

PUBLIC SAFETY 700 MHz RECEIVER FILTER 793 – 805 MHz

PR75-6CHS

Product Features

- Six poles combine preselector, designed to be used as a front-end protection in SMR trunking 700 MHz receivers
- Low insertion loss
- Strong rejection
- N(f) connectors are standard, other types available upon request



PR75-6CHS



Specification	Value
Type	Tx Filter
Frequency range	793 - 805 MHz
Insertion loss	0.5 dB max (793-805 MHz)
Rejection	70 dB min (763-775 MHz)
Noise suppression	75 dB min
Return loss	17 dB min
Power	200 W cont , 450 W peak
Connectors	N(f)
Temperature Range	5° to 140° F • -15° to +60° C
Dimension	19 x 2 x 6 inches • 482 x 51 x 153 mm
Weight	8 lbs • 3.6 kg
Mounting	For 19" normalized rack, 1 rack unit